

Surname	Centre Number	Candidate Number
First name(s)		0



**GCSE**

3500U10-1



**WEDNESDAY, 15 MAY 2024 – AFTERNOON**

**COMPUTER SCIENCE**

**Unit 1: Understanding Computer Science**

1 hour 45 minutes

For Examiner's use only		
Question	Maximum Mark	Mark Awarded
1.	4	
2.	8	
3.	8	
4.	8	
5.	6	
6.	6	
7.	6	
8.	12	
9.	10	
10.	10	
11.	10	
12.	12	
<b>Total</b>	<b>100</b>	

**INSTRUCTIONS TO CANDIDATES**

Use black ink or black ball-point pen. Do not use gel pen or correction fluid.

You may use a pencil for graphs and diagrams only.

Write your name, centre number and candidate number in the spaces at the top of this page.

Answer **all** questions.

Write your answers in the spaces provided in this booklet. If you run out of space, use the additional page(s) at the back of the booklet, taking care to number the question(s) correctly.

**INFORMATION FOR CANDIDATES**

The number of marks is given in brackets at the end of each question or part-question.

You are reminded of the need for good English and orderly, clear presentation in your answers.

The total number of marks is 100.

Some questions will require you to draw on your knowledge from multiple areas of your course of study.



JUN243500U10101

Answer **all** questions.

1. Tick (✓) the correct box to show if each statement about CPUs is TRUE or FALSE. [4]

Statement	True	False
The Control Unit (CU) decodes the program instruction in the Current Instruction Register (CIR).		
The Program Counter (PC) holds the address in main memory that is currently being read.		
RISC CPUs run at lower clock speeds than CISC CPUs.		
The slower the clock speed, the more power is generally required.		



2. Computer networks are constructed using specialised hardware.

(a) Tick (✓) the boxes to match the hardware with the correct description. [4]

Description	Hardware			
	Hub	Router	Switch	Bridge
Joins together two networks that use the same base protocols.	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
Copies all packets of data to all devices on the network.	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
Stores the addresses of computers on the network and transfers data between devices.	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
Analyses each data packet and sends it to the computer it was intended for.	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

(b) Identify **four** different types of computer network. [4]

- (i) .....
- (ii) .....
- (iii) .....
- (iv) .....



3. Compilation is a process for converting high level programs into machine code.

(a) Using the terms given complete the following sentences about the stages of compilation.

<b>Symbol</b>	<b>Lexical</b>	<b>Code</b>	<b>Translation</b>
<b>Optimisation</b>	<b>Assembly</b>	<b>Semantic</b>	<b>Syntax</b>

- (i) During ..... analysis keywords and identifiers are replaced by tokens. [1]
- (ii) During ..... analysis variables are checked to ensure they are the correct data type. [1]
- (iii) A ..... table is created to hold the addresses of variables and subroutines. [1]
- (iv) Code ..... may be employed to make the program more efficient. [1]



- (b) This pseudo code is part of a payroll system. The system calculates the net pay by subtracting deductions from the gross pay. The pseudo code includes errors. Identify **two** errors in the code. State each error type and correction needed. [4]

```
def CalcPay():

    Gross = input
    Tax = (Gross * 0.20)
    NatIns = (Gross * 0.10)
    Pension = (Gross * 0.10)
    Deducts = tax + NatIns + Pension
    NetPay = Gross + Deducts
```

(i) Type of error: .....

.....

Correction: .....

.....

(ii) Type of error: .....

.....

Correction: .....

.....

3500U101  
05



4. (a) Convert the following:

(i) the binary number  $1111\ 1100_2$  to hexadecimal. [2]

.....

.....

.....

.....

.....

(ii) the denary number  $138_{10}$  to hexadecimal. [2]

.....

.....

.....

.....

.....

(iii) the hexadecimal number  $5D_{16}$  to denary. [2]

.....

.....

.....

.....

.....



(b) State the effect of:

(i) An arithmetic shift left by one place.

[1]

.....

.....

.....

.....

.....

.....

(ii) An arithmetic shift right by two places.

[1]

.....

.....

.....

.....

.....

.....

3500U101  
07









**BLANK PAGE**

**PLEASE DO NOT WRITE  
ON THIS PAGE**





(d) Complete the truth table.

[4]

Examiner  
only

$P$	$Q$	$P \cdot Q$	$P + (P \cdot Q)$
0	0		
0	1		
1	0		
1	1		





(c) Explain why Parkwood Vale Motors have decided to encrypt the data they hold on their customers. [2]





(b) Describe a typical situation that requires the use of:

(i) a high-level language

[2]

.....

.....

.....

.....

.....

.....

(ii) a low-level language.

[2]

.....

.....

.....

.....

.....

.....



11. The chart is a representation of a simple sound wave. The wave is sampled every second and the amplitude is stored as a 4-bit binary number.



- (a) Complete the table to show how the wave would be represented in binary.

[5]

Time	1	2	3	4	5	6
Amplitude	12					
Binary	1100					



(b) (i) State the number of bits required to store the binary data from the completed table. [1]

.....

.....

.....

.....

(ii) Convert your answer from (b) (i) to bytes. [1]

.....

.....

.....

.....

(c) (i) Calculate the number of bytes required to store the data for the wave if four samples per second are taken. [1]

.....

.....

.....

.....

(ii) State the effect that increasing the sampling rate will have on the captured sound wave. [2]

.....

.....

.....

.....

.....

.....





A large rectangular area containing 25 horizontal dotted lines for writing.







